



**YMW-13T5** powered by:  
**3TNV84T BGGE**

**DESIGN SPECIFICATIONS**

- ✓High quality, reliable, long life and complete power unit.
- ✓compact design.
- ✓Easy start and maintenance possibility.
- ✓Every generating set is subject to a comprehensive test programme which includes full load testing and checking and proving of all control and safety shut down functions testing.
- ✓Fully engineered with a wide range of options and accessories: Electrical, mechanical, soundproof canopy and mobile units

Diesel Genset Features		P.F=0.8 3Phase	
Generating Set Performance		50Hz	
Service		Prime Power	Standby Power
Rated output	kVA	15.0	16.5
Active power output*	kW	12	13.2
Rated Speed	r.p.m	1500	
Standard Voltage	V	400/230	
Voltage available	V	380/220 - 415/240	

Performance data refer to Standard Reference Conditions of ISO 8528: +25 °C, 100m ALT, relative humidity 30%  
Power reduction acc.to DIN ISO 3046 Standard values: Above 100m ALT approx. 1% per 100m. Above 25 °C (77°F) approx. 4% per 10 °C (50°F).  
\*Considering cos phi=0.8

Prime Mover Performance		1500 r.p.m	
SERVICE		Prime Power	Standby Power
Rated output	KW	14	15.8
Manufacturer		Yanmar	
Model		3TNV84T BGGE	
4 stroke Diesel Engine - Injection type		Direct	
Aspiration type		Turbocharged Aspirated	
Cylinders, number and arrangement		3-L	
Bore*Stroke	mm	84X90	
Total Displacement	L	1.496	
Cooling system		Water	
Emission Certification		Tier 3	
Lube oil specifications		SAE 15 W 40	
Compression ratio		19	
Special fuel consumption	g/kw-h	245	
Oil capability	L	6.7	
Total coolant capacity	L	2	
Speed governor	Type	Mechanical	

① P.R.P. Prime Power - ISO 8528: PRIME POWER is the maximum power available during a variable power sequence, which may be run for an unlimited number of hours per year, between stated maintenance intervals. The permissible average power output during a 24 hours period shall not exceed 80% of the prime power. 10% overload available for governing purposes only.  
② Max Standby power - ISO 3046 Fuel Stop power: Power available for use at variable loads for limited annual time (500h), within the following limits of maximum operating time: 100% load 25h per year .90% load 200h per year. No overload available. Applicable in case of failure of the main in areas of reliable electrical network.

Synchronous Generator		1500 r.p.m	
Manufacturer		Guericke	
Model		GRK12G4	
Rated output	KW	12	
Poles	num	4	
Winding Connections (standard)		Star-serie	
Insulation	class	H	
Enclosure(according to IEC-34-5)		IP23	
Phases		3+N	
Voltage Regulaors		A.V.R (SX460)	
Steady voltage precision		within ±1.5% from no load to full loading with cosΦ=0.8-1.0	

\*Alternator used by GTL Gensets meet the requirements of following Standard: BS5000, VDE0530, NEMA MG1-32, IEC34, CA C22.2-100, AS1359







Generating Set Installation Data		1500 r.p.m	
<b>EXHAUST SYSTEM</b>			
Exhaust Gas Temperature at full load	°C	450	
	°F	842	
Exhaust gas flow	Kg/h	3.6	
Maximum allowed back pressure	mm / H2O	199	
<b>AIR REQUIREMENT</b>			
Air requirement for combustion at 100% load/rated speed	m³/min	1.3	
<b>ELECTRIC STARTING SYSTEM</b>			
Starting motor output	kw	1.2	
Battery		75D31	
Auxiliary voltage	V	12	
<b>LUBRICATION SYSTEM</b>			
Lube oil system including sump, filters, etc.	L	9.5	

**Standard Control Panel -EPmaster EPM4**

Protection, distribution, and automatic control panel, which starts the generator set when it detects a mains failure and stops it when the mains is restored with the control unit EPM4. It also starts and stops the group manually via a pushbutton or remote start-up by contact.

It has the following:

- ① Emergency stop push button
- ② Protections:
  - Circuit breaker (preheating resist.) 2P (16 A)
  - Protection fuses for control module
- ③ Voltage & speed trimmers
- ④ Battery charger
- ⑤ DC switch
- ⑥ Working Lamp switch
- ⑦ Distribution: Direct output of the circuit breaker
- ⑧ EPM6 & EPM6+ (cloud monitoring communication 4G) control and protection centre

		
GCB	Emergency Stop Button	Optional: ATS
		

### EPmaster EPM4

It has a digital LCD screen, which provides easy reading of the information regarding the Engine, Alternator, Mains and Charging. The controller meets all requirements for Auto Mains Failure (AMF) applications including remote communication and internet control, user configuration and complete genset monitoring and protection.

<p><b>• READINGS that can be made:</b></p> <p><b>Engine:</b> cooling temperature/oil pressure/revolution speed (rpm)/fuel level/battery voltage/battery alternator voltage/operating hours/number of start</p> <p><b>Alternator:</b> voltages between phases and between phases and neutral (L1-N, L2-N, L3-N)/voltages between phases and (L1-L2, L2-L3, L1-L3)/phase sequence</p> <p><b>Mains:</b> frequency/voltages between phases and between phases and neutral (L1-N, L2-N, L3-N)/voltages between phases and (L1-L2, L2-L3, L1-L3)/phase sequence</p> <p><b>Load:</b> Current (Ia, Ib, Ic) and each phase and total active power (kw)/reactive power (kvar)/apparent power (kva)/power factor/accumulated generator power (kwh, kvah, kvah)/output percentage with load (%)</p>	<p><b>• Protection of the engine and alternator, with the ALARMS activated:</b></p> <p><b>Engine:</b> low oil pressure/high coolant temperature/low and high battery Voltage./failure of the alternator to charge batteries/Low fuel level.</p> <p><b>Alternator:</b> low and high voltage/low and high frequency/overload /short-circuit/</p> <p><b>Mains:</b> over and under voltage and loss of phase</p> <p><b>• Control of the set:</b></p> <p>STARTS and STOPS the set AUTOMATICALLY when mains failure is detected and when it is restored, respectively. It can also operate MANUALLY and Auto Transfer Switch control</p>	<p><b>• Other characteristics:</b></p> <p>Event log, real-time clock, scheduled start &amp; stop generator (can be set as start genset once a day/week/month whether with load or not). Maximum 99 event logs can be memorized.</p> <p>With maintenance function. Types (date or running time) can be optional and actions (never, warning, or shutdown) can be set when maintenance time out.</p> <p>Equipped with CANBUS port and can communicate with J1939 engine. Not only can monitor frequently-used data (such as water temperature, oil pressure, speed, fuel consumption and so on) of ECU machine, but also control starting up, shutdown, raising speed and speed droop via CANBUS port</p> <p>RS485 communication interface enables "Three remote" functions (remote control, remote measuring and remote communication) according to MODBUS protocol.</p> <p>Parameter setting: parameters can be modified and stored in internal FLASH memory and cannot be lost even in case of power outage; most of them can be adjusted using front panel of the controller and also can be modified using PC via USB or RS485 port.</p>
---	--	---

### Standard Configuration & Option

Item	Standard	Option
Engine	Standard air filter	Heavy duty air filter
	Standard fuel filter	Air intake shutoff valve chawin type
	Standard oil filter	Intake air heater
	Low coolant level sensor	Oil temperature sensor
	Exhaust gases compensator	Diesel-powered heater
	24V Electrical system	Engine water heater
	Radiator with blowing fan	
	Electronic governor	
	Sender WT	
	Sender OP	
Alternator	Hot components and radiator guards	
	Mobile components guards	
	Self-excited and Self-regulated	Air inlet filter
	IP23 protection degree	IP44/IP54/IP55
	Insulation H class	Space heater/anti-condensation heater
Electrical system		Environment protection
		Temperature detectors
		Parallel operation
	Battery isolator switch	Distribution board with sockets kit and power busbar
	3 poles circuit breaker	4 poles circuit breaker
	Door opening alarm	Adjustable ELCB (Earth Fault)
Accessories	Battery charger 220-240V	Grounding rod
		ATS
	Water separator filter	Diverter valve kit for external fuel tank
	Low fuel level alarm	Automatic fuel refilling kit
	Oil extraction pump	Trailer
	Tool kit for maintenance	Residential silencer
	Voltage/Speed potentiometer	Electric engine fuel heater
No Expansion tank	Expansion tank for coolant water	

### Generating Set transport data

#### Dimensions (Open Skid Type) With Standard Fuel Tank



#### Over All Size

Length	mm	1320
Width	mm	604
Height	mm	1280
Shipping Volume	m3	1.02
Dry Weight	Kg	372
Fuel Tank Capacity	L	30

- √ The complete gen-set is mounted on whole on a heavy-duty fabricated, steel base frame.
- √ Antivibration pads are fixed between the engine/ alternator feet and the base frame;
- √ Base frame design incorporates an integral fuel tank.
- √ The generating set can be lifted or carefully pushed / pulled by the base frame;
- √ Dial type fuel gauge and drain plug on the fuel tank;
- √ Forklift pockets within base frame (up to 500kVA);

#### Dimensions (Silent Type) With Standard Fuel Tank



#### Over All Size

Length	mm	1480
Width	mm	790
Height	mm	1120
Shipping Volume	m3	1.31
Dry Weight	Kg	666
Fuel Tank Capacity	L	30

- √ All canopy parts are designed with modular principles.
- √ Without welding assembly
- √ All metal canopy parts are painted by electrostatic polyester powder paint.
- √ Doors on each side
- √ Thermally insulated engine exhaust system.
- √ Emergency stop push button outside of canopy.
- √ Easy maintenance and operation.



Tongan Industry Zone, Tongan District, Xiamen, China | Tel: +86 0592 7196398 | Fax: +86 0592 7898663 | E-mail: vicsun@cngtl.com | www.cngtl.com

